

REMARKS

This Amendment is submitted preliminary to the issuance of an Office Action in the present application and in response to the Official Action of April 24, 2006.

Claims 1-10 are pending in the application. Claims 1, 5 and 8 have been amended. Claims 2, 3, 6, 7 and 9 have been canceled. Claims 11-20 have been added. An amendment to the specification has been made. No fee is due.

It is noted that the drawings are objected to because of applicant's failure to show every feature set forth in claims 3-4, 6-9.

Claims 1-10 stand rejected under 35 U.S.C. §102(b) as being anticipated by U.S. Pat. No. 5,917,428 to Discenzo.

Record is also made of a telephonic interview between applicant's representative and the Examiner which took place on July 27, 2006. The Examiner is thanked for his help and assistance as well as for the courtesies extended to Counsel at that time. During the course of the interview, the present application was extensively discussed in light of the final rejection of claims 1 to 10, and as a result, applicant now submits this amendment to place the application in formal condition for allowance.

With respect to the objection to the drawings, applicant has now canceled claim 3, 6, 7 and 9. The Examiner agreed that Figs. 1 and 2 sufficiently show the presence of an infrared measuring system because of the illustration of the "detector 2" (see Figs. 1 and 2) and the "evaluation device 4" (see Fig. 2) which together define the measuring system. In addition, the Examiner also agreed that the reference to "rotating component", as set forth in claim 3, is sufficiently shown in Fig. 1 by way of the "rotor 7". The reference to "operating parameter" has been deleted from claim 8. In this context, reference is also made to Fig. 2 which depicts the operative interrelationship between the evaluation device and the fan in response to a temperature measurement by the detector.

With respect to the rejection of the original claims as being anticipated by Discenzo, applicant has amended claim 1 by setting forth the separate and spaced-apart disposition between the temperature radiation detector and the winding of the stator to effect the contactless measurement. There is no direct or indirect contact between the stator winding and the detectors. While Discenzo describes the provision of temperature sensors near the bearing components, there is still a direct connection between the sensors and the bearings, as the sensors are mounted in the motor end brackets that are in direct contact to the bearings.

The Examiner agreed that the subject matter of claim 1, as now on file, appears to be distinguishable over the prior art of record.

Applicant further submits herewith a new independent claim 11 which sets forth the separate and spaced-apart disposition between the temperature radiation detector and the rotor to effect the contactless measurement. There is no direct or indirect contact between the rotor and the detectors. Thus, claim 11 appears to be distinguishable over the prior art of record in a same manner as claim 1. Claims 12 to 15 have been added and set forth subject matter of claims 4, 5, 8 and 10.

In addition, applicant submits herewith a new independent claim 16 which sets forth the separate and spaced-apart disposition between the temperature radiation detector and permanent magnets on the rotor to effect the contactless measurement. While a reference to "permanent magnets" is absent from the original specification, applicant describes in paragraph [0015] of the instant specification that structure and operation of an electric machine are generally known to a person skilled in the art. It is therefore applicant's contention that the arrangement of permanent magnets on the rotor is generally known to the artisan so that no "new matter" is involved here. Reference is made, for example, also to pages 20, 21 of "ELECTRIC MOTOR Handbook, by H. Wayne Beaty and James L. Kirtley, Jr., published by McGraw-Hill, 1998, of which a copy is enclosed, and describing the attachment of permanent magnets to the rotor. In addition, reference is made to U.S. Pat. Nos. 4,674,178, issued June 23, 1987, and

4,746,827, issued May 24, 1988, of which a copy of each cover page is enclosed, and which describe the arrangement of permanent magnets on the outer periphery of the rotor.

As a consequence of the absence of any direct or indirect contact between the permanent magnets and the detectors, it is applicant's contention that claim 16 appears to be distinguishable over the prior art of record in a same manner as claim 1. Claims 17 to 20 have been added and set forth subject matter of claims 4, 5, 8 and 10.

In view of the above, each of the presently pending claims in this application is considered patentably differentiated over the prior art of record and believed to be in immediate conditions for allowance. Reconsideration and allowance of the present application are thus respectfully requested.

Should the Examiner consider necessary or desirable any formal changes anywhere in the specification, claims and/or drawing, then it is respectfully requested that such changes be made by Examiner's Amendment, if the Examiner feels this would facilitate passage of the case to issuance. If the Examiner feels that it might be helpful in advancing this case by calling the undersigned, applicant would greatly appreciate such a telephone interview.

Respectfully submitted,

By: 

Henry M. Feiereisen
Agent for Applicant
Reg. No. 31,084

Date: August 23, 2006
350 Fifth Avenue
Suite 4714
New York, N.Y. 10118
(212) 244-5500
HMF:af

McGraw-Hill Handbooks

ELECTRIC MOTOR Handbook

H. Wayne Beaty
James L. Kirtley, Jr.

Mc
Hill

McGraw-Hill



A Division of The McGraw-Hill Companies

Copyright © 1998 by The McGraw-Hill Companies, Inc. All rights reserved. Printed in the United States of America. Except as permitted under the United States Copyright Act of 1976, no part of this publication may be reproduced or distributed in any form or by any means, or stored in a data base or retrieval system, without the prior written permission of the publisher.

2 3 4 5 6 7 8 9 0 DOC/DOC 9 0 3 2 1 0 9

ISBN 0-07-035971-7

The sponsoring editor for this book was Larry Hager and the production supervisor was Tina Cameron. It was set in Century Schoolbook by Pro-Image Corporation.

Printed and bound by R. R. Donnelley & Sons Company.



This book is printed on recycled, acid-free paper containing a minimum of 50% recycled, de-inked fiber.

McGraw-Hill books are available at special quantity discounts to use as premiums and sales promotions, or for use in corporate training programs. For more information, please write to the Director of Special Sales, McGraw-Hill, 11 West 19th Street, New York, NY 10011. Or contact your local bookstore.

Information contained in this work has been obtained by The McGraw-Hill Companies, Inc. ("McGraw-Hill") from sources believed to be reliable. However, neither McGraw-Hill nor its authors guarantee the accuracy or completeness of any information published herein and neither McGraw-Hill nor its authors shall be responsible for any errors, omissions, or damages arising out of use of this information. This work is published with the understanding that McGraw-Hill and its authors are supplying information but are not attempting to render engineering or other professional services. If such services are required, the assistance of an appropriate professional should be sought.

Content

Preface xiii

Chapter 1 Electric Motors—J. Kirtley

- 1.1 Electric Motors
- 1.2 Types of Motor
 - 1.2.1 DC motors
 - 1.2.2 AC motors
- 1.3 Description of the Rest of the Book

Chapter 2 Terminology and Definitions—N. Ghai

- 2.1 Types of Motor
 - 2.1.1 AC and DC
 - 2.1.2 Synchronous and induction
 - 2.1.3 Salient-pole and cylindrical-rotor
 - 2.1.4 Single-phase and three-phase motors
 - 2.1.5 Other variations
- 2.2 Insulation System Classes
- 2.3 Codes and Standards

Chapter 3 Fundamentals of Electromagnetic Forces and Loss Mechanisms—J. Kirtley

- 3.1 Introduction
- 3.2 Energy Conversion Process
 - 3.2.1 Energy approach to electromagnetic forces
 - 3.2.2 Co-energy
 - 3.2.3 Generalization to continuous media
 - 3.2.4 Permanent magnets
 - 3.2.5 Electric machine description
- 3.3 Surface Impedance of Uniform Conductors
 - 3.3.1 Linear case
 - 3.3.2 Iron
- 3.4 References

$$W'_m = \int_{\text{vol}} -\nabla \cdot (\vec{A} \times d\vec{M}) d\upsilon + \int_{\text{vol}} (\nabla \times \vec{A}) \cdot d\vec{M} d\upsilon$$

Then, noting that $\vec{B} = \nabla \times \vec{A}$

$$W'_m = - \oint \vec{A} \times d\vec{M} d\vec{s} + \int_{\text{vol}} \vec{B} \cdot d\vec{M} d\upsilon$$

The first of these integrals (closed surface) vanishes if it is taken over a surface just outside the magnet, where \vec{M} is zero. Thus the magnetic co-energy in a system with only a permanent magnet source is

$$W'_m = \int_{\text{vol}} \vec{B} \cdot d\vec{M} d\upsilon$$

Adding current carrying coils to such a system is done in the obvious way.

3.2.5 Electric machine description

Actually, this description shows a conventional induction motor. This is a very common type of electric machine and will serve as a reference point. Most other electric machines operate in a fashion which is the same as the induction machine or which differ in ways which are easy to reference to the induction machine.

Consider the simplified machine drawing shown in Fig. 3.3. Most machines, but not all, have essentially this morphology. The rotor of the machine is mounted on a shaft which is supported on some sort of bearing(s). Usually, but not always, the rotor is inside. Although this rotor is round, this does not always need to be the case. Rotor




Figure 3.3 Form of electric machine.

conductors are shown, but sometimes the rotor has permanent magnets either fastened to it or inside, and sometimes (as in Variable Reluctance Machines), it is just an oddly shaped piece of steel. The stator is, in this drawing, on the outside and has windings. With most machines, the stator winding is the armature, or electrical power input element. (In dc and Universal motors, this is reversed, with the armature contained on the rotor.)

In most electrical machines, the rotor and the stator are made of highly magnetically-permeable materials: steel or magnetic iron. In many common machines such as induction motors, the rotor and stator are both made up of thin sheets of silicon steel. Punched into those sheets are slots which contain the rotor and stator conductors.

Figure 3.4 is a picture of part of an induction machine distorted so that the air-gap is straightened out (as if the machine had infinite radius). This is actually a convenient way of drawing the machine and, we will find, leads to useful methods of analysis.

What is important to note for now is that the machine has an air gap g which is relatively small (that is, the gap dimension is much less than the machine radius r). The air-gap also has a physical length ℓ . The electric machine works by producing a shear stress in the air-gap (with of course side effects such as production of "back voltage"). It is possible to define the average air-gap shear stress τ . Total developed torque is force over the surface area times moment (which is rotor radius)

$$T = 2\pi r^2 \ell(\tau)$$

Power transferred by this device is just torque times speed, which is the same as force times surface velocity, since surface velocity is $u = r\Omega$

$$P_m = \Omega T = 2\pi r \ell(\tau) u$$




Figure 3.4 Windings in slots.

United States Patent [19]

Patel

[11] Patent Number: 4,674,178

[45] Date of Patent: Jun. 23, 1987

[54] METHOD OF FABRICATING A PERMANENT MAGNET ROTOR

[75] Inventor: Navinchandra R. Patel, Rockford, Ill.

[73] Assignee: Sundstrand Corporation, Rockford, Ill.

[21] Appl. No.: 899,258

[22] Filed: Aug. 22, 1986

Related U.S. Application Data

[62] Division of Ser. No. 788,163, Oct. 16, 1985, Pat. No. 4,633,113.

[51] Int. Cl.⁴ H02K 15/14

[52] U.S. Cl. 29/598; 310/42; 310/43; 310/156

[58] Field of Search 29/598, 597; 310/42, 310/43, 45, 156, 261, 262, 271

[56] References Cited

U.S. PATENT DOCUMENTS

2,873,395 4/1954 Kober .
3,151,261 9/1964 Lee .

3,169,203 2/1965 Lavin et al. .
3,411,059 11/1968 Kaiwa .
3,445,700 5/1969 Prange et al. .
3,688,137 8/1972 Filhol .
3,707,638 12/1972 Nailen .
4,433,261 2/1984 Nashiki et al. .

FOREIGN PATENT DOCUMENTS

2440171 10/1968 Fed. Rep. of Germany .


Primary Examiner—Carl E. Hall

Attorney, Agent, or Firm—Wood, Dalton, Phillips, Mason & Rowe

[57] ABSTRACT

Loose or frayed fibers at the axial end of a fibrous wrap 42 about the periphery of rotor hub 10 mounting permanent magnets 22 are avoided by placing steps 40 between first and second diametral sections 36, 38 in side plates 32, 34 sandwiching the magnets 22 with the wrap preventing radial displacement of the magnets and the side plates preventing axial displacement.

4 Claims, 5 Drawing Figures



United States Patent [19]

Ochiai et al.

[11] Patent Number: 4,746,827

[45] Date of Patent: May 24, 1988

[54] ROTOR FOR ELECTRIC MOTOR

[75] Inventors: Izumi Ochiai; Hideo Hashida; Yoshio Asahino; Nobuhiko Yokota, all of Tochigi, Japan

[73] Assignee: Hitachi, Ltd., Tokyo, Japan

[21] Appl. No.: 15,630

[22] Filed: Feb. 17, 1987

[30] Foreign Application Priority Data

Feb. 28, 1986 [JP] Japan 61-41745

[51] Int. Cl.⁴ H02K 21/14

[52] U.S. Cl. 310/156; 310/261; 310/271

[58] Field of Search 310/156, 261, 262, 271

[56] References Cited

U.S. PATENT DOCUMENTS

2,060,259	11/1936	Spangler	310/156
2,071,536	2/1937	Kalin	310/156
2,432,436	12/1947	Morrill	310/156
4,633,113	12/1986	Patel	310/156

Primary Examiner—Donovan F. Duggan

Attorney, Agent, or Firm—Antonelli, Terry & Wands

[57]

ABSTRACT

A rotor for an electric motor including an iron core having collar portions at both end portions thereof, and a magnet placed on the outer periphery of said iron core. The magnet is held at both end portions thereof between the collar portions.

5 Claims, 2 Drawing Sheets

